

**Bullet Point Net Script – SER Emergency Radio Operations Center (EROC)**

**EROC TEAM RUNS NETS**


**NOTE • EMERGENCIES – USE PLAIN ENGLISH. SITUATION RPTS–USE Q CODES (FMT TANGO 9A/ 9M)**  
**(BOTH SYSTEMS MAY BE CONCURRENTLY USED DURING A NET. E.G., A FIRE NET WHICH IS ALSO RECEIVING QWA RPTS)**


SHINGLETOWN NET CONTROL (NCS) FIRE CONTROL IS : \_\_\_\_\_  
 IS: \_\_\_\_\_ (OR) **[DO “INCIDENT STATUS REPORT” EVERY 7 MIN]** (USE BULLET POINTS WITH KEY FACTS ONLY)

**➡ [IMMEDIATELY, DETERMINE INITIAL NET STRUCTURING. SELECT OPTIONS AS NEEDED]**

[STRUCTURE YOUR NET – OPTIONS]		If only impacting Village, then no need for Ham relay ON 10 OR EROC 58 RELAY. [USE COMMON SENSE]. OTHERWISE →	
<b>➡ WHEN PRIM ON EROC 9</b> [ NOTE: SER NETS ARE ONLY ON EROC 9, 10, OR EROC 58 ].	<b>MUST DO FOR PRIM RELAY</b>	<b>CONSIDER FOR MONITOR</b>	
	→ Need 10 RELAY	→Need EROC 58 MONITOR	
	OR → Need 10 ALPHA RELAY	→Need EROC 58 MONITOR	
	OR → Need EROC 58 RELAY	→Need 10 MONITOR	
<b>OTHERWISE, IF PRIM NET ON :</b>			
➡ IF EROC team goes FROM EROC 9 to EROC 3, 2, 1 or 4	→Need 9 Relay	CONTINUE WITH OPTIONS FROM ABOVE YOU ARE USING	
➡ WHEN PRIM NET ON HAM 10 or 10 A	→Need 9 Relay	AND → Need EROC 58 MONITOR	
➡ WHEN PRIM NET ON HAM EROC 58 (505) [NOTE: WHEN NET ON EROC 13 Freq., NCS MUST USE <b>EROC 58</b> FOR NET OPERATIONS SO ALL STATIONS CAN BE HEARD BY NCS.]	→Need 9 Relay	AND → Need 10 MONITOR	

**➡ START ACTIVATION [TONE OUT ON THE ESSENTIAL EROC TEAM MONITORING FREQUENCIES]**

[PICK BASED ON FACTS AND CIRCUMSTANCES] (DO NOT ENGAGE IN ANY DISCUSSION - GET TO THE NET!)	
[ FOR EMERGENCIES, E.G., FIRE NET ACTIVATIONS ]  • SEND TONE ON EROC <b>14</b> ( <u>IF APPLIES</u> – <u>ALERT FREQ</u> )	SAY - e.g., “Shingletown Fire Net ACTIVATED–Go to EROC 9 “NEED [10 RELAY ] [EROC 58 MONITOR]– GO TO EROC 9 & STAND BY” (YOUR IDENTIFIER) OR if on EROC 58 “Shingletown Fire Net Activated – Go to EROC 58” “ NEED [9 RELAY] [10 MONITOR] GO TO EROC 58, AND STANDBY” (YOUR IDENTIFIER)

[NOW GO TO PRIM NET CH. AS SELECTED ABOVE] • E.G., SEND TONE ON EROC <b>9</b> [OR 10 OR 10A OR EROC 58]  [ EROC 9 is the VILL PRIMARY NET FREQ. WHERE MOST NETS WILL BE RUN FROM; AND INTER-AREA RELAY FREQ.]	SAY “NET CONTROL ON EROC 9 ANY EMERG. TRAFFIC?” [OR ON: 10 OR 10A OR EROC 58] [if emergency traffic–assign STN to handle it & report back when done. Keep net moving] [ABOVE EXAMPLE ASSUMES PRIMARY NET IS ON EROC 9 WITH 10 RELAY AND EROC 58 MONITOR OPTION] [May pre-empt frequency for emergency] “FREQUENCY PRE-EMPTED FOR PRESENT EMERGENCY OF _____”
--	--

**➡ [ TRANSMIT SELECTED NET ACTIVATION AGENDA] ON PRIM. NET FREQ. (PICK WHAT APPLIES)**


- “THIS IS **Net Control ON EROC 9** ” OR [ON **10**] OR [ON **10 ALPHA**] OR [ON **EROC 58**]
- “THIS IS **FIRE CONTROL** ON ...: [FOR FIRE NET ACTIVATION]  
 (continue)
- EXAMPLES: • “SIT REP NET ACTIVATED USE FORMAT TANGO 9A OR 9M”  
 • “CONDUCT QWA PROCEDURE”  
 • “**FIRE NET** ACTIVATED” INCIDENT: \_\_\_\_\_

[OTHER ACTIVATION OPTIONS INCLUDE / MAY ACTIVATE MORE THAN ONE:]

DRILL	FIRE NET (NET CONTROL = “FIRE CONTROL”)
SITUATION RPTS–USE FMT TANGO 9A or 9M	SMOKE CHECK– USE FORMAT TANGO 4
CONDUCT QWA PROCEDURE	EARTHQUAKE NET – USE FMT TANGO 9A OR 9M

- “TAKING REPORTS IN 5 MINUTES” [COUNT DOWN BY MINUTES]. [ **FIRE NET** [IMMEDIATELY SET UP & START REPORTS]

**➡ [IN ALL CASES, IMMEDIATELY, START SETTING UP NET INFRASTRUCTURE AS NEEDED - BY TACTICAL]**

-  tone and say “NEED [10 RELAY]: [THIS IS BASED ON THE NET STRUCTURE OPTIONS SELECTED, ABOVE]  
 [OR 10 ALPHA RELAY OR 9 RELAY OR EROC 58 RELAY]
- “[10 RELAY] ... TONE ANNOUNCE ON [10], TRANSMIT AGENDA, REPORT WHEN DONE” ...  
 [DEPENDS ON NET STRUCTURE YOU SELECTED ABOVE [Note: Relay STN-use exact words of NCS / Fire Control]

- 🎵 tone and say **“NEED”** [SELECT **TACTICALS** AS NEEDED FOR NET YOU ARE OPERATING]

“CAL FIRE 20” (MONITORS CAL FIRE DISP – AT CH 20 in radios)	“160 TC”	“MAPPING”
“Sheriff 21” (monitors Sheriff – At CH 21 in radios)		
“TAC 11 28” (monitors Cal Fire tac 11 at CH 28 in radios)	“TAC _____” Cal Fire Tac CH #	“TRIANGULATION”
“GROUND _____”	GROUND _____	
“INTERNET WINDS”	“INTERNET CAMERA [SELECT CAMERA]”	“INTERNET - _____”

➡ **[CONDUCT NET OPERATIONS – START TAKING REPORTS ...]**

- **“TAKING VILLAGE REPORTS – FIRST STN GO”** [RECORD RPTS ON FMT T9M AND T9A AS APPROPRIATE]

➡ **[Note: For FIRE NETS,** REQUEST EACH TACTICAL TO PROVIDE REPORT DURING NET. THEN ABOUT EVERY 7 MINUTES PROVIDE **INCIDENT STATUS REPORT** AND HAVE “HAM RELAY” (E.G., “10 RELAY”) TRANSMIT YOUR **INCIDENT STATUS REPORT** EXACTY. IN YOUR INCIDENT STATUS REPORT SUMMARY GIVE APPROX LOCATION SO PEOPLE KNOW WHERE FIRE IS, ETC.)  
**MODIFY BELOW TO ACCOMMODATE A NET WHICH INCLUDES A FIRE NET. IF APPLICABLE, TAKE SIT REPS & QWA DURING PAUSES IN FIRE NET.**

- **“ANY VILLAGE RELAYS ...”**

- **“TAKING INTER –AREA REPORTS”** [E.G., MIDWAY, LONG HOLLOW, ...]  
 [NOTE: NET CONTROL SHOULD HAVE GOOD PROPOGATION TO GET INTER – AREA RPTS. IF NOT, ANOTHER STN MAY TAKE OVER NET. E.G., “NET CONTROL MAPPING... TAKING NET”. THEN RETURN NET TO NET CONTROL E.G., “NET CONTROL, MAPPING, ... YOUR NET”...]

- 🎵 tone to get attention (if needed) and say **“[10 RELAY], NET CONTROL ... REPORT”**  
 [ I.E., TAKE RELAY REPORT(S) FROM HAM]
- 🎵 tone to get attention (if needed) and say **“MAPPING, NET CONTROL ... IS YOUR SUMMARY READY?”**
- **“MAPPING GO” ...**
- 🎵 tone to get attention (if needed) and say **“TRIANGULATION, REPORT”** [ FIRE NET TO HAVE “TRIANGULATION”]
- **“ANY STATION DISAGREE WITH MAPPING SUMMARY / TRIANGULATION REPORT ?”**
- **“ALL STATIONS, NET CONTROL SUMMARY IS \_\_[BRIEF SUMMARY BY DIVISION]\_\_**
- **“NET CONTROL RECOMMENDATION IS \_\_\_\_\_”**  
 E.G.,: “NO ACTION”.  
 “DUE TO HIGH FIRE DANGER, ROUTINELY CONDUCT QWA PROCED. – RPT ONLY AS NECESSARY” ETC...), NO OTHER ACTION”.  
 “ELEVATED SCAN MONITORING DUE TO COMMUNCATIONS BLACKOUT”
- **“ANY STATION DISAGREE?”**
- 🎵 tone to get attention (if needed) and say **“[10 RELAY]... TRANSMIT NET CONTROL SUMMARY & RECOMMENDATION / [ TRIANGULATION REPORT]; DEACTIVATE; REPORT WHEN DONE”...**

➡ **[DEACTIVATIONS]**

- **“ MAPPING DEACTIVATE” ..... [DEACTIVATE EACH STATION TACTICAL YOU ACTIVATED, ABOVE]**
- **“ SITUATION REPORT NET IS DEACTIVATED”** [ INSERT NET YOU ARE DEACTIVATING].
- **“ALL STATIONS QSY SCAN”.**
- **“ NET CONTROL OUT”.** [ SCRIPT END ]